


IC-R20

Scan, Monitor, Record — The Pro's Scanner!

2 for 1, Dualwatch receive

Until the IC-R20, the capability of monitoring two frequencies required two radios. Whether you need to monitor local public safety, air traffic control, or at the track listening to two drivers, even the play by play from both the local TV and radio station is possible!

(See specifications for actual frequency ranges for Dualwatch receive.)




Shortwave to microwave, Wideband coverage

The IC-R20 covers 150kHz to 3304.999MHz* in SSB, CW, AM, FM and WFM modes. This covers AM/FM radio and TV broadcasts, wireless communications for boaters, aviation, conventional public safety and many other commercial services.

(* Depending on version, U.S.A. version is cellular blocked.)

4-hour digital recorder

The IC-R20 has an internal 32MB digital recorder capable of storing received communications. This feature is useful in a variety of ways, like recording a wireless microphone audio at a meeting. There is also a USB port to download to a computer for storage or to forward to a friend. (PC playback not possible)



CTCSS, DTCS tone signaling

When multiple users share the same channel, these users use specialized signaling to reduce interference from other users. The two popular signaling formats, CTCSS and DTCS are standard in the IC-R20. Tone scan is also possible.



Alphanumeric memory channels

With 1,000 regular memory channels, 200 automatic memory scan channels and 25 pairs of frequency scan edges, the IC-R20 makes it easy to identify received signals with the capability of programming a name to each channel.

11 hours of continuous receive*

Icom's energy efficient design allows the IC-R20 11* hours of continuous reception from the internal Li-Ion battery pack. Also, the IC-R20 can operate with 3 AA Alkaline cells, or longer operation as well as charging the internal battery pack is possible from either an optional cigarette lighter cable or the supplied AC adapter.

(* Single receive in FM mode, at Max. AF audio.)

See your signals

Sometimes hearing a signal is not enough, so the IC-R20 includes a band scope. The bandscope enables you to see signals around a monitored frequency. An additional function of the bandscope is the ability to hear the signal while sweeping a range, so you can see if the signal is modulated.



Scan features

The IC-R20 is Icom's fastest receiver with 100* channels per second scanning speed. You can tag memory channels into dynamic banks, ranging from Max. 100 channels per bank (Max. 26 banks) as well as link multiple banks for customized memory bank scanning. Additionally, the IC-R20 offers multiple scanning controls such as scan delay, scan resume for received signal notification.

(* In VFO mode.)



OTHER FEATURES

- VSC (Voice Squelch Control) opens the squelch only when a modulated signal is detected.
- Offset monitor capability for semi-duplex channel monitoring
- Auto squelch and squelch monitor capability
- Built-in attenuator and RF gain control
- Noise blanker, ANL (Auto Noise Limiter), AF filter
- AFC (Auto Frequency Control) function
- CI-V PC remote control capability with optional CT-17
- Built-in ferrite bar antenna for AM broadcast
- FM earphone cord antenna capability
- Dial speed-up function
- Auto power off and power save functions
- Key lock function
- Rotary selector and up/down buttons are reversible
- Weather channel and weather alert* (* U.S.A. version only)
- Preprogrammed with TV and popular shortwave channels

SPECIFICATIONS

GENERAL

- Frequency coverage : 0.150–1304.999, 1305.000–3304.999MHz*
(* Cellular blocked in the U.S.A. version.)
France 0.150–29.999, 50.2–51.2, 87.5–108, 144–146, 430–440, 1240–1300MHz
Dualwatch VFO A 0.150–469.999MHz (LSB, USB, CW, AM, FM, WFM modes)
VFO B 118–174.999, 330–1304.999MHz (AM, FM, WFM modes)
- Mode : LSB*, USB*, CW*, AM, FM, WFM (* 0.150–469.999MHz)
- No. of memory channels : 1250 (1000 regular, 50 scan edges and 200 auto memory write)
- Usable temperature range : -10°C to +60°C ; +14°F to +140°F
- Tuning steps : 0.01, 0.1, 5, 6.25, 8.33*, 9*, 10, 12.5, 15, 20, 25, 30, 50, 100kHz
(* Selectable depending on operating bands.)
- Battery requirement : BP-206 or 3×AA (R6) alkaline cells
- External power supply : 6.0V DC ±5% (with BC-149A/D, CP-18A/E)
- Current drain (at 3.7V DC) : Rated audio 150mA typ. (Backlight off)
(Single receive, IC rec OFF) Standby 100mA typ. (Backlight off)
Power save 35mA typ. (duty=1:4)
- Antenna impedance : 50Ω (BNC)
- Dimensions : 60(W)×142(H)×34.8(D) mm; 2³/₈(W)×5¹⁹/₃₂(H)×1³/₈(D) in
(projections not included)
- Weight (approx.) : 320g; 11.3oz (With antenna and BP-206)

All stated specifications are subject to change without notice or obligation.

RECEIVER

- Receiver system : Triple conversion superheterodyne + down converter
- Intermediate frequencies : 1st 266.7MHz, 429.1MHz, 2nd 19.65MHz, 3rd 450kHz
- Sensitivity (except spurious points; single receive):
FM 1.620– 4.999MHz 0.56μV 5.000– 221.999MHz 0.4μV
(12dB SINAD) 330.000– 832.999MHz 0.56μV 833.000–1304.999MHz 0.71μV
1330.000–2304.999MHz 5.6μV 2330.000–2999.999MHz 18μV
WFM 76.000– 108.000MHz 1.8μV 175.000– 221.999MHz 1.8μV
(12dB SINAD) 470.000– 769.999MHz 2.5μV
AM 0.495– 4.999MHz 2.2μV 5.000– 29.999MHz 1.4μV
(10dB S/N) 118.000– 135.999MHz 1.4μV
SSB, CW 0.495– 4.999MHz 0.4μV 5.000– 29.999MHz 0.25μV
(10dB S/N) 50.000– 53.999MHz 0.25μV 118.000– 146.999MHz 0.25μV
330.000– 469.999MHz 0.32μV
- Selectivity SSB, CW : More than 1.8kHz/–6dB
AM, FM More than 12kHz/–6dB, Less than 30kHz/–60dB
WFM More than 150kHz/–6dB
- AF output power (at 3.7V DC): 100mW typ. at 10% distortion with an 8Ω load
- External SP connector : 3-conductor 3.5 (d) mm (1/8") /8Ω

Supplied accessories

*depending on version

- BP-206* ● BC-149A/D* ● MB-98 ● Handstrap ● Antenna

OPTIONS

- **BP-206** Li-Ion BATTERY CELL ASSEMBLY
3.7V/1650mAh Lithium Ion battery pack.
- **BC-149A/D** WALL CHARGER
6V DC, 1A output AC adapter.
- **BC-156** DESKTOP CHARGER
Rapidly charges the BP-206 in 2.5 hours (approx.).
AC adapter, BC-123A/E supplied with the charger.
- **CP-18A/E** CIGARETTE LIGHTER CABLE
6V DC, 2A output from 12V cigarette lighter socket.
- **CT-17** CI-V LEVEL CONVERTER
For receiver remote control from a PC.
- **CS-R20** CLONING SOFTWARE (With USB cable)
Use a PC to easily edit stored memory channels, recorded contents and receiver settings.
(Microsoft® Windows® 98/Me/XP/2000)
- **LC-158** CARRYING CASE
Helps protect the receiver from scratches, etc.
- **MB-86** SWIVEL BELT CLIP
A fast and easy way to remove the receiver from your belt.
- **MB-98** BELT CLIP
Alligator type. Same as supplied.
- **SP-13** EARPHONE
Provides clear audio even in noisy environments.

Microsoft and Windows are registered trademarks of Microsoft Corporation in the U.S.A. and other countries.



Icom Inc.

1-1-32, Kamiminami, Hirano-ku, Osaka 547-0003, Japan Phone: +81 (06) 6793 5302□ Fax: +81 (06) 6793 0013

URL: <http://www.icom.co.jp/world/index.html>

Count on us!

Icom America Inc.

<Corporate Headquarters>□
2380 116th Avenue N.E., Bellevue, WA 98004, U.S.A.□
Phone□+1 (425) 454-8155□ Fax: +1 (425) 454-1509□
URL□: <http://www.icomamerica.com>
<Customer Service>□ Phone: +1 (425) 454-7619

Icom Canada

Glenwood Centre #150-6165 Highway 17, □
Delta, B.C., V4K 5B8, Canada□
Phone□+1 (604) 952-4266□ Fax: +1 (604) 952-0090□
URL□: <http://www.icomcanada.com>

Icom (Australia) Pty. Ltd.

A.B.N. 88 006 092 575□
290-294 Albert Street, Brunswick, Victoria, 3056, Australia□
Phone□+61 (03) 9387 0666□ Fax: +61 (03) 9387 0022□
URL□: <http://www.icom.net.au>

Icom New Zealand

146A Harris Road, East Tamaki, Auckland, New Zealand□
Phone□+64 (09) 274 4062□ Fax: +64 (09) 274 4708□
URL□: <http://www.icom.co.nz>

Icom (Europe) GmbH

Communication Equipment□
Himmelgeister Str. 100, D-40225 Düsseldorf, Germany□
Phone□+49 (0211) 346047□ Fax: +49 (0211) 333639□
URL□: <http://www.icomeurope.com>

Icom Spain S.L.

Crta. de Gracia a Manresa Km. 14,750□
08190 Sant Cugat del Valles Barcelona, Spain□
Phone□+34 (93) 590 26 70□ Fax: +34 (93) 589 04 46□
URL□: <http://www.icomspain.com>

Icom (UK) Ltd.

Unit 9, Sea St., Herne Bay, Kent, CT6 8LD, U.K.□
Phone□+44 (01227) 741741□ Fax: +44 (01227) 741742□
URL□: <http://www.icomuk.co.uk>

Icom France S.a

Zac de la Plaine, 1, Rue Brindejonc des Moulinais□
BP 5804, 31505 Toulouse Cedex, France□
Phone□+33 (5) 61 36 03 03□ Fax: +33 (5) 61 36 03 00□
URL□: <http://www.icom-france.com>

Asia Icom Inc.

6F No. 68, Sec. 1 Cheng-Teh Road, Taipei, Taiwan, R.O.C.□
Phone□+886 (02) 2559 1899□ Fax: +886 (02) 2559 1874□
URL□: <http://www.asia-icom.com>

Beijing Icom Ltd.

1305, Wanshang Plaza, Shijingshan Road, Beijing, China□
Phone□+86 (010) 6866 6337□ Fax: +86 (010) 6866 3553□
URL□: <http://www.bjicom.com>



Icom Inc. (Japan), is an ISO 9001 and ISO 14001 certification acquired company.

Your local distributor/dealer: